



TDS12502

Remote Control

The TDS12502 is an all-in-one, user friendly infra-red remote control for home automation control. User friendly interface, because the remote control automatically adapts its functions to the place where you are.

Application example: When the central lights for every room are programmed on button 1 of the according input interfaces, clicking button 1 on your remote control will change the central light. If you go to another room with a TELETASK wall panel, and you click the same button number 1, the central light in the new room will be changed instead of the former one.

APPLICATION

To be used where remote control of the functions on a touch panel or other TELETASK interface with infrared receiver is desired.

There are more functions to be controllable on the remote control than on a touch panel or digital input interface.

To be used in combination with an IR receiver (in touch panel or external with TDS12125 or TDS12127)

CHARACTERISTICS

The remote control is equipped with 8 buttons for the control of 8 functions. The controlled function depends on the TELETASK interface that receives the IR command.

8 numeric buttons for the control of direct functions.

Shift button: ' ': in combination with the 8 numeric buttons, the extra functions are controlled (button 9-16 on a LATUS).

Shift button 'house': in combination with the 8 numeric buttons, the 'MASTER' functions are controlled.

Audio – video buttons.

Battery

CR2025 (3V Lithium) – supplied with the unit. Compatible with CR2032

SETTINGS

IR functions via PROSOFT

©+ ↑ B&O (455kHz)

©+↓ Standaard (36kHz)

POWER CONSUMPTION

Estimated battery lifetime: 1 year (no warranty on the battery)

DIMENSIONS

46 W x 175 H x 8 D (mm)

NET | GROSS WEIGHT

0,040 kg | 0,150 kg

PACKAGING CONTENT

TDS12502

STORAGE

Temperature

-20°C to +65°C

Relative humidity

15% to 85%

IP PROTECTION RATE

IP20

OPERATING RANGE

Temperature

0°C to +50°C max.

Relative humidity

5% to 80% at 25°C (non-condensing ambient)