

TDS14030

Beolink interface



Interface to the B&O BEOLINK system (passive link systems – power amplifiers).

Important remark: only units with a passive link are controllable.

Application:

To control a multi room B&O system by standard buttons, touch panels, TELETASK remote control and all connected systems. At the other hand it is possible to activate eight functions via the 'light' functions on the B&O remote control. Up to four zones can be controlled by one B&O interface. The basic audio functions of each (passive link) zone are controllable by the TELETASK systems.

Characteristics:

Connecting up to 4 'passive link' of B&O.
Connecting up to 4 IR-LINKS from TELETASK touch panels.
Control 8 TELETASK functions through the light key of the B&O remote control.
Control the audio functions of the passive link of the concerning room through the TELETASK remote control.

Settings:

Functions:	With PROSOFT Suite
AUTOBUS address:	Through rotary switches Tens + Units

Installation:

To be set up in the neighbourhood of the passive link amplifiers.

Connections:

AUTOBUS:	By enclosed AUTOBUS connector.
IR-LINK inputs:	By 4-pole miniature connector.
Passive IR-LINK B&O:	By means of screw terminals (3 wires).

Power Consumption:

Max. 70 mA

Dimensions:

216 W x 87 H x 55 D (mm)
12 units

Net | Gross weight:

0,560 kg

IP protection rate:

IP20

Schematic Drawing:

